



Quick Start Guide

Smart Series Intensity Control



P/N 83-200055 Rev A



Smart Series LED Lights can be adjusted for intensity via a pulse width modulating signal (PWM) sent to pin 5 of the input connector (referenced to DC ground). The required signal must have a constant frequency where the duty cycle of the pulse width is changed, thereby varying the amount of current to the LEDs. See Smart Series Specification, Configuration docs and Quick Start Guide on the Omron Microscan website for detailed signal requirements.

Should users not have a PWM signal available in their system, a device manufactured by Red Lion Controls [pn AFCM 0000], can convert a variety of standard analog signals to a PWM signal output.

Model AFCM- Analog to Frequency Converter Model

- VOLTAGE/CURRENT TO FREQUENCY CONVERTER
- 3-WAY ISOLATION OF INPUT / OUTPUT SIGNALS
- UNIVERSAL CONVERSION MODULE - INPUTS AND OUTPUTS SELECTED VIA DIP SWITCH SETTINGS
- ULTRA SLIM DESIGN – ONLY 0.244" WIDE
- 19 to 30 VDC POWER


DESCRIPTION

The configurable analog to frequency converter is used to convert analog standard signals to frequency signals or pulse width modulated (PWM) signals. Input signal ranges are 0 - 20 mA, 4 - 20 mA, 0 - 10 mA, 2 - 10 mA, 0 - 10 V, 2 - 10 V, 0 - 5 V, or 1 - 5 V.

The DIP switches are accessible on the side of the housing and allow the following parameters to be configured:

- Input signal
- Output values
- Output type (frequency or PWM)
- Filter type (for smoothing interferences on the input signal)
- Input over/under range fault detection

DIMENSIONS in inches (mm)




ORDERING INFORMATION

MODEL NO.	DESCRIPTION	PART NUMBER
AFCM	Analog to Frequency Converter Module	AFCM0000

WIRING CONNECTIONS

Primary power is connected to terminals 7 or 3 (19.2 – 30 VDC) and 8 or 4 (GND 3). For best results, the Power should be rela-

tively “clean” and within the specified variation limits. Drawing power from heavily loaded circuits or from circuits that also power loads that cycle on and off, should be avoided. The input signal is connected to terminal 1 (In UI) and 2 (GND 1). Connections for the output signal is on terminals 5 (Out f) and 6 (GND 2).



CONFIGURATION

DIP Switch S1

Using DIP switch S1, you can set the input values, and the values for Moving Average Filter and Over sampling.

1	2	3	4	ANALOG IN
				0 - 10V
	ON			1 - 5V
		ON		0 - 5V
	ON	ON		2 - 10V
ON			ON	0 - 20mA
ON	ON		ON	4 - 20mA
ON		ON	ON	0 - 10 mA
ON	ON	ON	ON	2 - 10mA

The moving average filter can group values (1, 2, 4, 6) using moving window averaging to form a new measured value. In moving window averaging, the average of a fixed number of measured values is taken, whereby the oldest value is always dropped and the most recent added.

In order to smooth the measured values, an average can be formed from several measured values (1, 10, 50, 100). This process is called Over sampling. In oversampling, the average is updated every time the selected number of values is reached.

5	6	MOVING WINDOW AVERAGING
		1 value
ON		2 values
	ON	4 values
ON	ON	6 values


7	8	OVER SAMPLING
		1 value
ON		10 values
	ON	50 values
ON	ON	100 values

DIP Switch S2

Using DIP switch S2, you can set the output values, the output type and fault detection.

Output Signals Frequency Output:


Variable frequency/period duration T



1	2	3	4	FREQUENCY OUTPUT
				0 - 10 kHz
ON				0 - 5 kHz
	ON			0 - 2.5 kHz
ON	ON			0 - 1 kHz
		ON		0 - 500 Hz
ON		ON		0 - 250 Hz
	ON	ON		0 - 100 Hz
ON	ON	ON		0 - 50 Hz

PWM Output (Pulse Wide Modulation):

Variable pulse to pause ratio/fixed period duration T



1	2	3	4	PWM OUTPUT
			ON	7.8 Hz
ON			ON	3.9 Hz
	ON		ON	1.9 Hz
ON	ON		ON	977 Hz
		ON	ON	488 Hz
ON		ON	ON	244 Hz
	ON	ON	ON	122 Hz
ON	ON	ON	ON	61 Hz

Change can only be read by PWM input meters

Fault Detection

7	8	INPUT UNDER RANGE
		Freeze at 100% measuring range start value
ON		105% measuring range end value
	ON	110% measuring range end value
ON	ON	Fault detection OFF (stops at start value)


5	6	INPUT OVER RANGE
		Freeze at 100% measuring range end value
ON		ON 105% measuring range end value
	ON	110% measuring range end value
ON	ON	Fault detection OFF (continues past end value)

INSTALLATION

The unit is equipped with a universal mounting foot for attachment to standard DIN style top hat (T) profile rail according to EN50022 - 35 x 7.5 and 35 x 15. The unit should be installed in a location that does not exceed the maximum operating temperature and provides good air circulation. Placing the unit near devices that generate excessive heat should be avoided.

T Rail Installation

To install the AFCM on a "T" style rail, angle the module so that the top groove of the "foot" is located over the lip of the top rail. Push the module toward the rail until it snaps into place. To remove a module from the rail, insert a screwdriver into the slot on the bottom of the "foot", and pry upwards on the module until it releases from the rail.



SPECIFICATIONS

INPUT

- INPUT SIGNAL RANGE** (Configurable): 0 - 20 mA, 4 - 20 mA, 0 - 10 mA, 2 - 10 mA, 0 - 10 V, 2 - 10 V, 0 - 5 V, 1 - 5 V
- MAX. INPUT SIGNAL:**
Current inputs: 100 mA
Voltage inputs: 30 VDC
- INPUT RESISTANCE:**
Current inputs: 50 , approx.
Voltage inputs: 110 K , approx.

OUTPUT

- OUTPUT SIGNAL RANGE** (Configurable):
Frequencies: 0 - 10 kHz, 0 - 5 kHz, 0 - 2.5 kHz, 0 - 1 kHz, 0 - 500 Hz 0 - 250 Hz, 0 - 100 Hz, 0 - 50 Hz
PWM: 7.8 kHz, 3.9 kHz, 1.9 kHz, 977 Hz, 488 Hz, 244 Hz, 122 Hz, 61 Hz
- MIN. LOAD:**
Frequency: 6 K
PWM: 2 K
- MAX. LOAD CURRENT:** 20 mA
- OUTPUT:** NPN open collector transistor
- MAX. SWITCHING VOLTAGE:** 30 V
- OVER-RANGE/UNDER-RANGE FAULT DETECTION:**
Configurable
- OUTPUT PROTECTION:** Short circuit and polarity protection

GENERAL DATA

- SUPPLY VOLTAGE:** 19.2 - 30 VDC
- NOMINAL VOLTAGE:** 24 VDC
- CURRENT CONSUMPTION:** < 10 mA
- POWER CONSUMPTION:** < 200 mW
- TRANSMISSION ERROR:** < 0.1%
- TEMPERATURE COEFFICIENT (MAX.):** < 0.02%/K
- STEP RESPONSE:**

0% to 99%: < 15 msec + (1/T)
With Largest Filter: < 1 sec + (1/T)

- TEST VOLTAGE (INPUT / OUTPUT / SUPPLY):** 1.5 kV, 50 Hz, 1 min
- AMBIENT TEMPERATURE RANGE:**
Operation: -20 t +65°C (-4 to 148°F)
Storage: -40 to +85°C (-4 to 183°F)
- FAULT DETECTION:** Red LED under clear cover top
- CERTIFICATIONS AND COMPLIANCES:**

Conformance With EMC Guideline 89/336/EEC And Low Voltage Directive 73/23/EEC

Immunity to Interference According to EN 61000-6-2

Discharge of static electricity (ESD) EN 61000-4-2 Criterion B1

Electromagnetic HF field EN 61000-4-3 Criterion A2

Fast transients (Burst) EN 61000-4-4 Criterion B1

Surge voltage capacities (Surge) EN 61000-4-5 Criterion B1

Conducted disturbance EN 61000-4-6 Criterion A2

Noise Emission According to EN 61000-6-4

Noise emission of housing EN 55011 Class A3

1 Criterion B: Temporary impairment to operational behavior that is corrected by the device itself.

2 Criterion A: Normal operating behavior within the defined limits.

3 Class A: Area of application industry.

- CONNECTIONS:** Wire Gauge: 24-12 AWG, Stripping length: 0.47" (12 mm)
- CONSTRUCTION:** Polybutylenterephthalate PBT, black
- MOUNTING:** Standard DIN top hat (T) profile rail according to EN50022- 35x7.5
- WEIGHT:** 2 oz. (54 g)



UL Recognized Component,
File # E257265



SAFETY SUMMARY

The device may only be installed and put into operation by qualified personnel. The corresponding national regulations must be observed.



Caution: Be sure that all connections are secure BEFORE applying power. Power down BEFORE disconnecting cables.



Important: All specified wire colors apply to Omron Microscan Cables. If non-Omron Microscan cables are used, it is the customer's responsibility to make sure the illuminator is connected per the specified connector pin numbers.